

350 Series AC/DC Clamp Meters



Fluke 353



Fluke 355

True-RMS, 2000 A Clamp Meters for industrial and utility applications

Confidently take reliable readings with the true-rms, Fluke 353/355 Clamp Meters; the tools of choice for high current measurement up to 2000 A. The extra-wide jaw easily clamps around large conductors, typically found in high current applications. The rugged design and CAT IV 600 V, CAT III 1000 V ratings add an extra element of protection when taking high-powered measurements.

Accurate peak measurements can be taken using the in-rush current mode - ideal for motors and inductive loads. The 355 also measures voltage and resistance, making this the most versatile tool for utilities, electrical contractors and industrial service technicians.

Features

	353	355
True-RMS measurements	●	●
Display backlight	●	●
Motor start-up current	●	●
Min/Max/Average	●	●
Voltage AC/DC		●
Resistance measurement		●
Continuity measurement with beeper		●

Specifications

(Check the Fluke web for detailed specifications)

Functions	Range	353	355
Current AC/DC	0-40.00 A	1.5% ± 15 counts	1.5% ± 15 counts
	0-400.0 A	1.5% ± 5 counts	1.5% ± 5 counts
	0-2000 A; 1400 AC rms		
Crest Factor		2.4	2.4
Voltage AC/DC	0-4.000 V	1% ± 10 counts	1% ± 5 counts
	0-40.00 V		
	0-400.0 V		
	0-600 V AC rms		
Resistance	0-1000 V DC	1.5% ± 5 counts	
	0-400.0 Ω		
	0-4.000 kΩ		
	0-40.00 kΩ		
Continuity beeper	Appr. ≤ 30 Ω		
Frequency	5.0Hz to 100.0Hz		0.2% ± 2 counts
	100.1Hz to 999Hz		0.5% ± 5 counts



True RMS

Included Accessories

Fluke 353: C43 Soft Meter Case, 6 AA batteries, users manual

Fluke 355: C43 Soft Meter Case, 6 AA batteries, TL224 SureGrip® Silicone Test Lead Set, TP2 Slim Reach Test Probe Set (2 mm), AC285 SureGrip® Alligator Clip Set, users manual

Power Supply:

6 x 1.5V AA NEDA 15A or IEC LR6
100 hours (with typical usage, backlight off)

Battery Life:

Size (HxWxD): 300 mm x 98 mm x 52 mm
Jaw opening: 58 mm
Weight: 0.814 kg
Two year warranty

Ordering information

Fluke 353 AC/DC Clamp Meter
Fluke 355 AC/DC Clamp Meter

Recommended Accessories



TL223 (Fluke 355)
See page 100



L215 (Fluke 355)
See page 101



宇宏企業股份有限公司 RADIOTEK CORPORATION

台北縣三重市重新路五段609巷16號6樓之1

TEL: 02-22782269 FAX: 02-22782059

Home page : www.radiotek.com.tw

E-mail : salesmag1@rdmail.com.tw